

- Compatible remote control, code remote control.
- It memorizes two different codes one button each.



## INITIALIZING

- 1 - Place the original remote control X in front of **BABY-R** at 4 cm of distance
- 2 - Press and keep pressed button **1** the LED is **green**
- 3 - Press **four** times the button **2** and the led will be **green**
- 4 - Release all buttons

**Green** LED flashes shortly every 2,5 sec.  
(8 flashes) for maximum 20sec. **which.....**

## CLONE THE FIX AND ROLLING CODE WITHOUT THE SOURCE CODE

**All rolling code remote or fix code in the list which can be downloaded in the web site, excluding the remote controls with the source code, see next paragraph.**

- 5 - Press and release the button to be copied in the remote and wait for a while until the led **BABY-R** is flashing quickly to confirm the correct learning copy process.
- 6 - While the LED flashes (*max 20sec.*), press and keep press the corresponding button on **CARTY-R** where you need to copy the original code until the LED switched off to confirm the right learning copy process.

## IN THE RADIO RECEIVER

Choose "MODE" in the table: **MODE FAST** or **MODE ENTER** or **MODE MANUAL**

## CLONE THE ROLLING FAAC / GENIUS WITH THE SOURCE CODE

**FAAC 433 / 868**      **GENIUS 433 / 868**

*The remote control must be a MASTER, if you press the button the LED flashes twice instead fix light.*

- 5 - Press and keep pressed the button to be copied until the Led of **BABY-R** lights on.
- 6 - Release the button and wait.
- 7 - LED of **BABY-R** flashes shortly each 2sec.  
*This indicate that it is time to memorize the **source code**.*
- 8 - Press simultaneously buttons **1** and **2** of FAAC or GENIUS remote control and release them
- 9 - LED of the remote control FAAC or GENIUS flashes (max 9sec.)
- 10 - Press and keep pressed the button to be copied of FAAC or GENIUS remote control and wait for a few seconds until the LED **BABY-R** flashes quickly.
- 11 - Press the button which need to be copied and keep pressed until the LED of **BABY-R** switched off.

## IN THE RADIO RECEIVER

Check the right function of the new remote control **BABY-R**

See **MODE FAST** or **MODE ENTER** pressing twice the memorized button.



**CLONE REMOTE CONTROL ROLLING BFT WITH SOURCE CODE BFT**

**BFT**

- 5 - Press and keep pressed the corresponding button of original remote control until the LED **BABY-R** will lit on
- 6 - Release the button and wait.
- 7 - After a while LED of **BABY-R** then it will flash every 2 seconds.  
*This indicate that it is necessary to put a **source code***
- 8 - **Press at the same time buttons 1 and 2 (or push with a pin the hidden button in the back side) of BFT remote control and release until the LED BFT will turn on.**
- 9 - LED **BABY-R** flashes quickly
- 10 - Press and keep pressed the button **BABY-R** where you need to memorize the code and wait for a few seconds until the LED switched off to confirm that the code has been successfully copied
- 11 - Activate learning process in the receiver

**IN THE RADIO RECEIVER**

Check the correct operation of the new **BABY-R** see **BFT: MODE FAST**

**CLONE REMOTE CONTROL ROLLING V2 WITH SOURCE CODE V2**

**V2**

- 5 - Press and keep pressed the corresponding button on original remote control until the LED **BABY-R** will lit on
- 6 - Release the button and wait.
- 7 - LED of **BABY-R** will flash shortly for 2 seconds  
*This indicate the **source code** is required*
- 8 - **Press simultaneously buttons 1 and 2 of V2 remote control and release them both**
- 9 - LED of **BABY-R** will flash quickly
- 10 - Press and keep pressed the button **BABY-R** where you need to memorize the code and wait for a few seconds until the LED turned off to confirm the correct copy process.
- 11 - Activate learning process in the receiver

**IN THE RADIO RECEIVER**

Check if the new **BABY-R** is working see **V2: MODE FAST**



Scan QR to  
download info  
about the  
CARTY-R  
BABY-R

- !!! If the LED flashes three times and switched off, it means that the code has not been memorized, repeat from step n°2.
- !!! The memory **BABY-R** is completely rewritable.
- !!! To memorize more buttons **CARTY-R**, repeat the operation from step n°2.

**CONFORMITY DECLARATION**

Declare under our sole responsibility that the product **EB Technology** **BABY-R** to which this declaration relates is in conformity with all the essential requirements of the European Directive 1999/5/EC (R&TTE) and the Council Recommendation 1999/915/EC (Human Exposure). The conformity with the essential requirements of the above Regulations has been verified against the following harmonised standards: • EN 300 220-2 • EN 301 489-1 • EN 301 489-3 • EN 60950-1:2006 +A11:2009+A12:2010+A12:2011 • EN 50371:2002

**TECHNICAL DETAILS**

Power supply: battery 3V CR2032  
Range up: from 60 to 100 mt.  
UE Frequencies: 433,92MHz / 868,30MHz