

FacePass

Standalone Facial Recognition System

Quick Guide (v1.0)




ANVIZ®

Copyright © 2001-2012 Anviz Global Inc.

ANVIZ® is registered trademark of Anviz Global, and cannot be used without the permission of Anviz. Due to the consistent improving of the product, this specification and appearance is subject to change without notice.

Packing List

1 Product



2 Instruction Package



3 Accessory Package



4 Wire



Notice

1. Please keep the product away from the magnetic field, and avoid causing any damage to the device.
2. Please don't take apart the device or change the circuitry it.
3. Please test device connection with software before installing on the wall.
4. Please don't install with power in order to avoid causing any damage to the device.
5. Please use the original power supply or refer to the instruction to get the right power supply.
6. Damage to the equipment caused by incorrect operation and wiring are not under warranty.

Installation Environment

Before Installation:

The FacePass working temperature: 0°C---45°C , working humidity: 20%---80%

Direct sunlight would cause great impact on the face recognition performance. So the terminal is not allowed to be installed outside. Please install the terminal indoor and avoid strong light shining straight into the camera.

Installation Steps

Step 1: Installation Position

The best verification distance of FacePass is 11.8"-31.5" (30-80 cm)


and the best image capture angle of the camera is level: $\pm 20^\circ$, vertical: $\pm 20^\circ$.

The recommended installation height is 43.3" (110cm) from the ground.

In this position the FacePass can capture body height ranging is 57"-76.8"

(145-195 cm) the person's face image is in valid verify distance.

For the actual installation height please refer to the user's height.



Step 2: Holing fot the Steel Bracket

- (1) Please refer to the size of the steel bracket, mark out the screw and wiring holes. Make sure the back board is on horizontal position.
- (2) Drill the hole (Recommended dia.6 mm).






Figure (3) Fixed Steel Bracket

Step 3: Fixing Steel Bracket

- (1) Fix the steel bracket on the wall with self tapping screws.
- (2) Pull all the cables out from the wiring hole of the steel bracket.

Step 4: Fixing the Terminal

- (1) Connect cables with the terminal.
- (2) Push down the terminal into the rabbet of the steel bracket.
- (3) Fix the terminal with screws.



Enroll User




①

Power on the terminal to enter Input Page. Press **[0/#]** to Admin verification page.



②

Input default password "88888888" and press **[#/*]** to enter Main Menu Page.




③

Click "User" option to enter User Manage Page.



④

Click "New" to enter User Enroll Page.



⑤

In the User Enroll Page click "Name", "ID" and "Pwd" input box.



⑥

The terminal will enter words Input Page via the touch screen to input user information. And press **[#/*]** back to User Enroll Page.




⑦

Press "Enroll" to capture user face image.



⑧

Before starting capture user face the terminal will display prompt on the screen.



⑨

During face image capturing process, please keep your face in the yellow frame and move face forward and backward slightly till enrolling successfully.

Yellow frame: the valid recognition area;

Blue frame: the valid image capturing area;

Red frame: the invalid image capturing area.

Face Recognition




①

In the Input page click **[#/*]** to enter Face Recognition Page.




②

If enable body induction in the terminal it will automatically switch to Face Recognition Page when user stands in front of the terminal.



③

According to the terminal instruction please keep your face in the yellow frame.



④

Face verification succeed.

1 Year Limited Warranty

Anviz Global Inc., (the "Company") warrants to the original purchaser that the Company's products for one (1) year from the date of purchase to be free of structural and mechanical defects due to faulty materials or workmanship under normal use and service.

For Warranty Service

Please register your product at <http://www.anviz.com/members/login.html> for follow warranty service and technical support service.

All defective products must notify the Company's International Support Department, The International Support Department will decide to either have the product returned for repair or replacement. The defective product must be returned to the Company within thirty (30) days of failure and with a description of the failure and Return Merchandise Authorization (RMA) number supplied by the Company. To receive a RMA number and obtain assistance on where to deliver the hardware, please E-Mail at: support@anviz.com. Any product returned with out RMA will be refused. During the warranty period, the Company agrees to repair or replace, at its sole option, without charge to Original Purchaser, any defective component part of the hardware. To obtain service, Original Purchaser must return the hardware to the Company in original product packaging or in an adequate container for shipping. The postage, shipping, and insurance charges incurred in shipping to the Company will be paid by Original Purchaser, and all risk for the hardware shall remain with the Original Purchaser until such time as Company takes receipt of the hardware. Upon receipt, the Company will promptly repair or replace the defective unit, and then return said unit to Original Purchaser, postage and shipping prepaid. The Company may use reconditioned or like-new parts or units, at its sole option, when repairing any hardware. Repaired products shall carry the same amount of outstanding warranty as from original purchase, or ninety (90) days, whichever is greater. Any claim under the warranty must include dated proof of purchase or invoice. In any event, the Company's liability for defective hardware is limited to repairing or replacing the hardware.

What Does This Warranty Not Cover?

The following costs expenses and damages are not covered by the provisions of this limited warranty:

- (1) Shipping and freight expenses required to return the Company.
- (2) Failures, defects, or damage (including, but not limited to, any security failure or loss of data) caused by any third party product, service, or system connected or used in conjunction with the Product.
- (3) Any other incidental, indirect, special or punitive damages, whether based on contract warranty, tort (including, but on limited to, strict liability or negligence) patent infringement, or otherwise, even if advised of the possibility of such damages.
- (4) The Product use for purposes for which they are not designed or intended.
- (5) The Product which have been subjected to alteration, abuse, misuse, negligence or accident.
- (6) The product has been improperly stored, installed, maintained or operated.
- (7) The product has been used in violation of written instructions provided by the Company.
- (8) The product has been subjected to improper temperature, humidity or other environmental conditions or which, based on the Company's examination, do not disclose to the Company's satisfaction non-conformance to the warranty.

Additionally, this warranty DOES NOT COVER scratches abrasions or deterioration due to the use of paints, solvents or other chemicals.

This warranty gives you specific legal right, and you may also have other right as otherwise permitted by law. If this Product is considered a consumer product, Please be advised that some laws do not allow limitations on incidental or consequential damages or how long an implied warranty lasts. So that the above limitations may not full apply. Refer to your local laws for your specific right under this warranty.

www.anviz.com



Please scan this bar code to win Anviz vCard

ANVIZ®
Intelligent Security